

LD 26: Group Do Not Disturb

Overlay program 26 allows Do Not Disturb groups to be created, modified, and printed.

Prompts and responses

Prompt	Response	Comment
REQ	aaa	Request
TYPE	DND	Type of data block = DND (Do Not Disturb Group)
CUST	xx	Customer number associated with this data block
GPNO	0-99	Group Number or new Group Number to be formed
TOGP	0-99	Move to Group number
GRPx	0-99	Number of next Group to be moved
STOR	x...x	DN to be Stored
RMOV	x...x	Remove DN

Alphabetical list of prompts

Prompt	Response	Comment	Pack/Rel
CUST	xx	Customer number associated with this data block as defined in LD 15.	dndg-1
GPNO	0-99 <cr>	Group Number or new Group Number to be formed Print all Group Numbers. Prompted when REQ = PRT.	dndg-1
GRPx	0-99 <cr>	Number of next Group to be moved Proceed to next prompt.	dndg-1
REQ	CHG END MOV MRG NEW OUT PRT REM	Action Request Change existing data block. Exit Overlay program. Move a DN from one DND Group data block to another Group data block. Merge existing Group data blocks into a new Group (the old groups will still exist) data block. Create a New data block. Remove data block. Print DND Group data block. Remove an entry from a Group data block.	dndg-1
RMOV	x...x G0-G99	Remove DN Up to 4 digits, up to 7 digits with Directory Number Expansion (DNXP) package 150. Remove Group number	dndg-1
STOR	x...x G0-G99	DN to be stored Up to 4 digits, up to 7 digits with Directory Number Expansion (DNXP) package 150. Group number to be stored. Numbers may be added when REQ is CHG.	dndg-1
TOGP	0-99	Move To Group number	dndg-1
TYPE	DND	DND Group data block type	dndg-1